## **AUDIO TRANSFORMER**

Ruggedized



- Typical Applications: Telephone Sets, PBX's, DLC Systems, Central office Switches
- Optimized insertion loss and return loss for audio frequencey range, including voicebane
- ullet Designed for  $600\Omega$  line impedance
- Frequency response: ± 0.5dB @300Hz~3.5KHz
- Moisture Sensitivity Level: 1

Electrical Specifications @ 25 °C – Operating Temperature $-$ 40 °C to $+85$ °C						
Part Number	Primary Impedance $1 \text{KHz}/1.0 \text{Vrms SEC } @600 \ \Omega \\ (\Omega \pm 10\%)$	Insertion Loss 1KHz/1.0Vrms (dB MAX)	DCR (Ω MAX)		Turns Ratio (±2%)	Hi-Pot @1.0mA / 1s (VAC MIN)
PL3141	600	1.5	(2-4)	(7-9)	(2-4):(7-9)	Pri : Sec
			55	67	1:1	1000


Note: 1. Optional Tape & Reel packaging can be ordered by adding a "T" suffix to the part number (i.e. PL3141 becomes PL3141T).

2. Suffix "NL" for RoHS (Sn100 Lead Finish); i.e. PL3141NL

### Mechanical

# **Electrical Schematic**

### PL3141



#### **For More Information**

iNRCORE,LLC 311 Sinclair Road Bristol, PA 19007-6812 U.S.A Tel: + 1.215.781.6400 Fax: +1.215.7816430

#### Global Sales Representatives and Locations:

http://www.inrcore.com

Performance warranty of products offered on this data sheet is limited to the parameters specified. Data is subject to change without notice. Other brand and product names mentioned herein may be trademarks or registered trademarks of their respective owners. © Copyright, 2020. iNRCORE, LLC. All rights reserved.



www.inrcore.com